

0.8mm TYPE A

<p>08CH-A-XX-IDC 0.8mm IDC HOUSING WITH PRE-INSTALLED CONTACTS</p> <p>08CH-A-08-IDC</p> <p>Replace (XX) with No. of positions A=.031 [0.80] X No. of Positions -1 B=.031 [0.80] X No. of Positions + .031 [0.80]</p>	<p>08SH-A-XX-TS-SMT 0.8mm VERTICAL SMT HEADER</p> <p>08SH-A-08-TS-SMT</p> <p>Replace (XX) with No. of positions A=.031 [0.80] X No. of Positions -1 B=.031 [0.80] X No. of Positions + .031 [0.80]</p> <p>Recommended PCB Layout</p>
--	---

1.00mm TYPE A

<p>1CH-A-XX 1.00mm CRIMP HOUSING</p> <p>1CH-A-04</p> <p>Replace (XX) with No. of positions A=.039 [1.00] X No. of Positions -1 B=.039 [1.00] X No. of Positions + .118 [3.00]</p>	<p>1CTA-R 1.00mm TERMINAL</p> <p>1CTA-R</p> <p>Recommended wire size 32-28 awg.</p>
---	---

<p>1SH-A-XX-TS-SMT 1.00mm VERTICAL SMT HEADER</p> <p>1SH-A-04-TS-SMT</p> <p>Replace (XX) with No. of positions A=.039 [1.00] X No. of Positions -1 B=.039 [1.00] X No. of Positions + .078 [2.00]</p> <p>Recommended PCB Layout</p>	<p>1SH-A-XX-TR-SMT 1.00mm RIGHT ANGLE SMT HEADER</p> <p>1SH-A-04-TR-SMT</p> <p>Replace (XX) with No. of positions A=.039 [1.00] X No. of Positions -1 B=.039 [1.00] X No. of Positions + .078 [2.00]</p> <p>Recommended PCB Layout</p>
--	---