

<p>15CH-A-XX 1.5mm CRIMP HOUSING</p> <p>15CH-A-10</p> <p>A=.060 [1.50] X No. of Positions -1 B=.060 [1.50] X No. of Positions + .059 [1.50]</p>	<p>15CTA-R 1.5mm CRIMP TERMINAL</p> <p>Recommended wire size 26-30 awg.</p>
<p>15SH-A-XX-TS 1.5mm VERTICAL HEADER</p> <p>15SH-A-04-TS</p> <p>A=.019 [0.50] X NO. of Positions -1 B=.019 [0.50] X NO. OF SPACES +.059 [1.50]</p> <p>Recommended PCB Layout</p>	<p>15SH-A-XX-TR 1.5mm RIGHT ANGLE HEADER</p> <p>15SH-A-04-TR</p> <p>A=.019 [0.50] X NO. of Positions -1 B=.019 [0.50] X NO. OF SPACES +.059 [1.50]</p> <p>Recommended PCB Layout</p>
<p>15SH-A-XX-TS-SMT 1.5mm VERTICAL SMT HEADER</p> <p>15SH-A-04-TS-SMT</p> <p>A=.060 [1.50] X No. of Positions -1 C=.060 [1.50] X No. of Positions + .118 [3.00]</p> <p>Recommended PCB Layout</p>	<p>15SH-A-XX-TR-SMT 1.5mm RIGHT ANGLE SMT HEADER</p> <p>15SH-A-04-TR-SMT</p> <p>A=.060 [1.50] X No. of Positions -1 C=.060 [1.50] X No. of Positions + .118 [3.00]</p> <p>Recommended PCB Layout</p>

<p>15CH-B-XX 1.5mm CRIMP HOUSING</p> <p>15CH-B-05</p> <p>A = .059 [1.50] X No. of Positions -1 B = .059 [1.50] X No. of Positions +.043 [1.10]</p>	<p>Recommended wire size 28-24 awg.</p> <p>15CTB-R 1.5mm CRIMP TERMINAL</p> <p>15CTB-R</p>
<p>15SH-B-XX-TS-SMT 1.5mm VERTICAL SMT HEADER</p> <p>15SH-B-04-TS-SMT</p> <p>A = .059 [1.50] X No. of Positions -1 B = .059 [1.50] X No. of Positions +.051 [1.30]</p> <p>Recommended PCB Layout</p>	<p>15SH-B-XX-TR-SMT 1.5mm RIGHT ANGLE SMT HEADER</p> <p>15SH-B-04-TR-SMT</p> <p>A = .059 [1.50] X No. of Positions -1 B = .059 [1.50] X No. of Positions +.051 [1.30]</p> <p>Recommended PCB Layout</p>
<p>2CH-B-XX 2mm CRIMP HOUSING</p> <p>2CH-B-10</p> <p>Positions: 2 thru 15 A = .079 [2.00] x No. of Positions -1 B = .079 [2.00] x No. of Positions +.063 [1.60]</p>	<p>Recommended wire size 28-22 awg.</p> <p>2CTB 2mm CRIMP TERMINAL</p> <p>2CTB-R</p>
<p>2SH-B-XX-TS 2mm VERTICAL HEADER</p> <p>2SH-B-10-TS</p> <p>A = .079 [2.00] x No. of Positions -1 B = .079 [2.00] x No. of Positions +.078 [2.00]</p> <p>Recommended PCB Layout</p>	<p>2SH-B-XX-TR 2mm RIGHT ANGLE HEADER</p> <p>2SH-B-10-TR</p> <p>A = .079 [2.00] x No. of Positions -1 B = .079 [2.00] x No. of Positions +.078 [2.00]</p> <p>Recommended PCB Layout</p>