

<p> <math>A = .433 [11.00] \times \text{No. of Ports} + .100 [2.54]</math>  <math>B = .433 [11.00] \times \text{No of Ports} + .020 [0.50]</math>  <math>C = .433 [11.00] \times \text{No of Ports} - 1</math> </p>		<p><b>TYPE 2</b> 6p4c 6p6c</p> <p><b>MTJG-2-642X1</b></p> <p><b>Recommended PCB Layout</b></p>
<p> <math>A = .459 [11.65] \times \text{No. of Ports} + .100 [2.54]</math>  <math>B = .459 [11.65] \times \text{No of Ports} + .020 [0.50]</math>  <math>C = .459 [11.65] \times \text{No of Ports} - 1</math> </p>		<p><b>TYPE 2B</b> 6p4c 6p6c</p> <p><b>MTJG-2-642BX1</b></p> <p><b>Recommended PCB Layout</b></p>
<p> <math>A = .571 [14.50] \times \text{No. of Ports} + .100 [2.54]</math>  <math>B = .571 [14.50] \times \text{No of Ports} + .020 [0.50]</math>  <math>C = .571 [15.50] \times \text{No of Ports} - 1</math> </p>		<p><b>TYPE 2C</b> 6p4c 6p6c</p> <p><b>MTJG-2-642CX1</b></p> <p><b>Recommended PCB Layout</b></p>