

HFTR

Dimensions: .118 [3.00], .126 [3.20], .185 [4.70]

Recommended PCB Layout

Dimensions: .050 [1.27], $\phi .027$ [0.70], .200 [5.10] TERMINATED HEIGHT, .118 [3.00]

HFTR-26-T

Part No.	A		B	
	in	mm	in	mm
HFTR-10	.413	10.50	.200	5.08
HFTR-12	.464	11.80	.250	6.35
HFTR-14	.515	13.10	.300	7.62
HFTR-16	.563	14.30	.350	8.89
HFTR-20	.665	16.90	.450	11.43
HFTR-22	.712	18.10	.500	12.70
HFTR-26	.815	20.70	.600	15.24
HFTR-30	.917	23.30	.700	17.78
HFTR-34	1.015	25.80	.800	20.32
HFTR-40	1.165	29.60	.950	24.13
HFTR-44	1.263	32.10	1.050	26.67
HFTR-50	1.413	35.90	1.200	30.48

HFDP

Dimensions: .303 [7.70], .050 [1.27], .100 [2.54], .075 [1.90], .075 [1.90], .075 [1.90], .094 [2.40], .275 [7.00]

Recommended PCB Layout

Dimensions: .050 [1.27], .100 [2.54], .075 [1.90], .075 [1.90], .075 [1.90], $\phi .032$ [0.81], .280 [7.10] TERMINATED HEIGHT, .303 [7.70]

HFDP-80-T

Part No.	A		B	
	in	mm	in	mm
HFDP-30-T	0.938	23.83	0.700	17.78
HFDP-50-T	1.438	36.53	1.200	30.48
HFDP-68-T	1.888	47.96	1.650	41.91
HFDP-80-T	2.188	55.58	1.950	49.53
HFDP-100-T	2.688	68.28	2.450	62.23

FDH

Dimensions: .157 [4.00], .394 [10.00], .228 [5.80] AFTER ASSEMBLY

Recommended PCB Layout

Dimensions: .300 [7.62], .050 [1.27], .100 [2.54], $\phi .039$ [1.00]

FDH-34-T

Part No.	A		B	
	in	mm	in	mm
FDH-10-T	.689	17.50	.450	11.43
FDH-14-T	.889	22.58	.650	16.51
FDH-16-T	.989	25.12	.750	19.05
FDH-20-T	1.189	30.20	.950	24.13
FDH-26-T	1.489	37.82	1.250	31.75
FDH-34-T	1.889	47.98	1.650	41.91
FDH-40-T	2.189	55.60	1.950	49.53
FDH-50-T	2.689	68.30	2.450	62.23
FDH-60-T	3.189	81.00	2.950	74.93