

<p>Technical drawings of the Secure Digital Socket (No Standoff) showing top, side, and bottom views with dimensions:</p> <ul style="list-style-type: none"> <li>Top View: 1.114 [28.30] (width), .583 [14.80] (height)</li> <li>Side View: .087 [2.20] (thickness), .659 [16.75] (height), .134 [3.40] (width)</li> <li>Bottom View: 1.264 [32.10] (width), 1.193 [30.30] (width)</li> </ul>		<p><b>SECURE DIGITAL SOCKET</b></p> <p>Part Nos. Available SD-09-SG-0 (No Standoff) SD-09-SG-1 (2.0mm Standoff)</p> <p>Recommended PCB Layout</p>
<p>Technical drawings of the Secure Digital Socket with Metal Cover showing top, side, and bottom views with dimensions:</p> <ul style="list-style-type: none"> <li>Top View: 1.035 [26.30] (width), .838 [21.30] (height)</li> <li>Side View: .984 [25.00] (height)</li> <li>Bottom View: 1.122 [28.5] (width), 1.071 [27.20] (width), .112 [2.85] (height), .098 [2.50] (width), .827 [21.00] (width)</li> </ul>		<p><b>SECURE DIGITAL SOCKET WITH METAL COVER</b></p> <p>Part Nos. Available SDM-09-SG-0 (No Standoff) SDM-09-SG-1 (2.0mm Standoff)</p> <p>Recommended PCB Layout</p>
<p>Technical drawings of the Secure Digital Socket Push-In / Push-Out showing top, side, and bottom views with dimensions:</p> <ul style="list-style-type: none"> <li>Top View: .120 [3.05] (width), .567 [14.40] (width), .610 [15.50] (width)</li> <li>Side View: 1.165 [29.60] (height)</li> <li>Bottom View: .348 [8.85] (height), .348 [8.85] (height), .407 [10.35] (height), .423 [10.75] (height), .559 [14.20] (width), .602 [15.30] (width)</li> </ul>		<p><b>SECURE DIGITAL SOCKET PUSH-IN / PUSH-OUT</b></p> <p>Part Nos. Available SDP-09-SG-0 (No Standoff) SDP-09-SG-1 (2.0mm Standoff)</p> <p>Recommended PCB Layout</p>